

RATING CHARTS

ENCLOSED L SERIES

INPUT		OUTPUT				TYPE	APPROXIMATE WEIGHT (POUNDS)		
VOLTS	HERTZ	VOLTS	CONSTANT CURRENT LOAD		CONSTANT IMPEDANCE LOAD		NET	SHIPPING	
			MAX. AMP.	MAX. KVA.	MAX. AMP.				MAX. KVA.
120	60	0-132	1.75	.23	---	---	3 lb.	6 lb.	
120	50/60	0-140	4.5	.63	---	---	10 lb.	11 lb.	
120	50/60	0-140	10	1.4	---	---	14 lb.	15 lb.	

LINE CORRECTOR SERIES**

INPUT		OUTPUT		MANUALLY OPERATED				MOTOR DRIVEN		APPROXIMATE WEIGHT (POUNDS)	
VOLTS	HERTZ	VOLTS	MAX. AMP.	MAX. KVA.	TYPE	APPROXIMATE WEIGHT (POUNDS)		TYPE	AVAILABLE SPEEDS (SECONDS) AT 60 HZ □ □ □	APPROXIMATE WEIGHT (POUNDS)	
						NET	SHIPPING			NET	SHIPPING
95-135	50/60	115	57	6.6	LC2106D	66	81	MDLC2106D	5, 15, 30, 60	79	99
95-135	50/60	115	144	16.6	LC2115E	117	202	MBLC2115E	5, 15, 30, 60	197	227
195-255	50/60	230	36	8.3	LC2207D	88	83	MDLC2207D	5, 15, 30, 60	81	101
205-250	50/60	230	130	29.9	LC2228E	183	208	MBLC2228E	5, 15, 30, 60	212	243
400-520	50/60	480	45	20.7	LC2418E	177	202	MBLC2418E	5, 15, 30, 60	197	227
195-255	50/60	230	63	25.1	LC3220YD	204	229	MDLC3220YD	5, 15, 30, 60	222	252
195-255	50/60	230	145	57.8	LC3245YE	551	631	MBLC3245YE	5, 15, 30, 60	565	650
195-255	50/60	230	188	74.9	LC3270DE	560	670	MBLC3270DE	5, 15, 30, 60	580	695
400-520	50/60	480	35	27.9	LC3425YD	210	235	MDLC3425YD	5, 15, 30, 60	228	258
400-520	50/60	480	100	79.7	LC3475YE	536	616	MBLC3475YE	5, 15, 30, 60	550	635
420-500	50/60	450	148	118	LC34100YE	536	616	MBLC34100YE	5, 15, 30, 60	550	635

single phase

three phase

**Line Correctors may also be used as limited range transformers. Input voltage is the output voltage shown in the chart and output voltage is the input voltage shown in the chart.

*Maximum voltage limited by saturation characteristics of transformer core.

160 hertz only.

□ □ Speeds are 20 percent slower at 50 hertz.

AUXILIARY EQUIPMENT

TYPE	DESCRIPTION	TYPE	DESCRIPTION	TYPE	DESCRIPTION
14096-000	Raise-Lower Switch	26602-008	Control Potentiometer For FR501B	T5579B	3-Gang Paralleling Choke for 136B, 236B, 246 Series
PD120B	Position Detector	T6076	Transformer for Full Range Regulator Controllers	T5587	Paralleling Choke supplied with all 1156D-1256D Series
26602-008	Position Control Potentiometer	T6340	Transformer for Full Range Regulator Controllers	T6053	2-Gang Paralleling Choke for 146 Series
T6068	Transformer for Positioner Detector	62110001	Potentiometer Adapter Kit for 100 Series	T6065	3-Gang Paralleling Choke for 146 Series
FR501B*	Full Range Regulator Controller For A.C. Voltage Control	30111-000	Potentiometer Adapter Kit for 12 Series		
FR501BMP*	Full Range Regulator Controller with Meter and Control	15000B	2-Gang Paralleling Choke 136B, 236B, 246 Series		
FR501BDC*	Full Range Regulator Controller For D.C. Voltage Control				

*Add suffix X when ordering for use with X-suffixed motor-driven POWERSTAT Variable Transformers.

REPLACEMENT BRUSHES

UNIT TYPE ¹	BRUSH TYPE	UNIT TYPE ²	BRUSH TYPE	UNIT TYPE ¹	BRUSH TYPE	UNIT TYPE ²	BRUSH TYPE	UNIT TYPE ¹	BRUSH TYPE	UNIT TYPE ²	BRUSH TYPE
		116C	RB116M	226	RB226	146	RB146				
						246	RB246	Q116U	RBQ116	Q217U	RBQ217
10C	RB10B	117C	RB117B	136B, LC2106D, LC3220YD	RB136	1156D, LC2115E, LC2418E, LC3245YE	RB1156B	Q117U	RBQ117	LW136B	RBLW136
12	RB12	216C	RB216B							10C-40	RB10B-40
21	RB21	217C	RB217B	236B, LC2207D, LC3425YD	RB236	1256D, LC2228E, LC3270DE, LC3475YE, LC34100YE	RB1256B	Q216U	RBQ216	21-40	RB21-40
22	RB22	126	RB126							116C-40	RB116B-40

¹ Includes also 3-gang units and variations such as Enclosed, Oil-Cooled and Explosion-proof types.