

Model #: AVR750U

AVR Series Line-Interactive UPS System - Affordable line-interactive protection for PCs and workstations



Highlights

750VA ultra-compact line-interactive UPS

Maintains 120V nominal output over an input range of 83V to 147V
Workstation-optimized features include USB port (HID-PDC compliant),
single-line TEL / DSL surge suppression, 6 battery- and surge-protected outlets
and 6 additional surge-only outlets (12 total)

Space saving right-angle input plug

Input: NEMA 5-15P (120V 15A) / Output: 12 NEMA 5-15R (120V)

2-year product warranty

Description

Tripp Lite's AVR750U line-interactive UPS offers complete protection for PCs, workstations and other sensitive electronics in an ultra-compact, mountable housing. Prevents data loss and system downtime by providing battery-supported AC output during blackouts and Automatic Voltage Regulation (AVR) during brownouts and overvoltages. Includes 12 output receptacles, 4 of which are widely spaced to accommodate large transformer blocks without obscuring adjacent outlets. 6 outlets feature full battery support and surge suppression, protecting computers, monitors and other vital system components from power loss. 6 additional outlets with surge suppression only are ideal for printers and other peripherals not requiring battery support. Single-line telephone suppression jacks protect modems, fax machines, cordless phones or other equipment with a DSL or standard dialup RJ-11 phone line connection. USB port with included cable and PowerAlert monitoring software enables safe unattended system shutdown in case of extended power failure. HID-compliant USB interface enables integration with built-in power management and auto-shutdown features of Windows and Mac OS X. Audible alarm and front panel LEDs offer status information regarding line and battery power operation. 750VA/450 watt power-handling ability supports entry-level PCs for up to 35 minutes during power failures. 2-year warranty.

Applications

Basic PCs for home/home-office use, network workstations, audio/video equipment, home entertainment systems and other sensitive electronic devices.

Package Includes

AVR750U UPS System

PowerAlert Software CD-ROM, USB cable, RJ-11 phone cable Instruction manual with warranty information

Features

AVR750U line-interactive UPS offers protection from blackouts, brownouts and surges on both AC and Tel/DSL line connections
Built-in Automatic Voltage Regulation (AVR) boosts brownouts as low as 83V and reduces overvoltages up to 147V back to usable 120V nominal levels

12 outlets, 4 of which are widely spaced to accommodate large transformer blocks without obscuring adjacent outlets 6 battery-supported outlets protect computers, monitors and vital system peripherals, plus 6 additional surge suppression-only outlets for printers and other system accessories not requiring battery support

Provides battery-derived AC output during blackouts, voltage boost during brownouts and voltage reduction during overvoltages

750VA/450 watt power-handling ability supports a variety of PCs, workstations and other sensitive electronics

Supports entry-level PC systems up to 35 minutes during blackout conditions

Built-in single-line Tel/DSL line surge suppression protects modems, fax machines or cordless phones

USB port, included USB cable and PowerAlert software offer safe, unattended shutdown without data loss during extended outages

HID-compliant USB port enables integration with built-in power management and auto shutdown features of Windows and Mac OS X

Supports Tripp Lite's Watchdog system service to restore operation to locked equipment through soft reboot of application/OS or hard power off/on reboot of connected equipment - ideal for unattended kiosk applications

Hot-swappable user battery replacement supported via battery access door

Space-saving, ultra-compact housing fits almost anywhere

Keyhole mounting flanges enable secure wallmount installation

Specifications

Voltage compatibility 60Hz Frequency compatibility 60Hz OUTPUT Voutput VA 750 Output wats 450 Output voltage 2120VAC Output voltage Sine wave 120V +8% / -21% (line mode) / PWM sine wave 115V +/-5% (battery mode) Output frequency regulation LINE MODE: Passes line frequency of 60Hz +/-10% BATTERY MODE: Inverter output regulated to 60Hz +/-0.5Hz Outled quantity / type 12 MEMA 5-15R Input 12A Input connection type NEMA 5-15P (space saving right-angle plug) Input cord length 6 ft / 1.8m Recommended Electrical Service 20V 15A BATTERY 10 min (375VA) Bal fload runtime 10 min (375VA) DC system voltage 12 VOC Typical battery itiespan 3 to 6 years, depending on usage lifespan Battery recharge rate 2 to 4 hours to reach 90% charge Replacement Battery RBC51 VOLTAGE REGULATO Automatic voltage is reduced by 12% as line voltage increases to 128V or higher cordered or 20 voltage is reduced by 12% as line voltage fereases to 128V or higher Overvoltage correction Dutput voltage is boos	SYSTEM OVERVIEW				
Compatibility 750 Output Watts 450 Output matts 450 Output voltage 120VAC Output voltage Sine wave 120V +8% / -21% (line mode) / PWM sine wave 115V +/-5% (battery mode) regulation Output frequency regulation LINE MODE: Passes line frequency of 60Hz +/-10% BATTERY MODE: Inverter output regulated to 60Hz +/-0.5Hz fregulation Outlet quantity / pp 12 NEMA 5-15R INPUT MEMA 5-15P (space saving right-angle plug) Input connection type NEMA 5-15P (space saving right-angle plug) Input cord length 6 ft / 1.8m Recommended lectrical Service 120V 15A BATTERY Full load runtine 3 min (750VA) Half load runtine 10 min (375VA) DC system voltage 12VDC Typical battery [isepane 3 to 6 years, depending on usage [isepane sattery recharge rate 2 to 4 hours to reach 90% charge Replacement Battery active page regulation maintains 120V nominal over an input voltage range of 83V to 147V Voltage regulation melantains 120V nominal over an input voltage range of 83V to 147V Overvoltage correction Output voltage is reduced by 12% as line voltage increases to 128V or higher	Voltage compatibility	120VAC			
Output VA 750 Output watts 450 Output nominal voltage 120VAC Output voltage regulation Sine wave 120V +8% / -21% (line mode) / PWM sine wave 115V +/-5% (battery mode) Output voltage regulation LINE MODE: Passes line frequency of 60Hz +/-10% BATTERY MODE: Inverter output regulated to 60Hz +/-0.5Hz Outbut quantity / type 12 NEMA 5-15R INPUT Maximum input amps 12A Input connection type NEMA 5-15P (space saving right-angle plug) Input cord length 6 ft / 1.8m Recommended Electrical Sortia 120V 15A Input cord length 3 min (750VA) BATTERY 10 min (375VA) DC system voltage 12VDC Typical battery lifespan 3 to 6 years, depending on usage lifespan Battery recharge rate 2 to 4 hours to reach 90% charge Replacement Battery carridge RBC51 VOLTAGE REGULATION Voltage regulation maintains 120V nominal over an input voltage range of 83V to 147V Overvoltage Output voltage is reduced by 12% as line voltage increases to 128V or higher correction Output voltage is boosted by 14% as line voltage decreases to 104V or lower		60Hz			
Output watts 450 Output nominal voltage 120VAC Output voltage regulation Sine wave 120V +8% / -21% (line mode) / PWM sine wave 115V +/-5% (battery mode) regulation Output frequency regulation LINE MODE: Passes line frequency of 60Hz +/-10% BATTERY MODE: Inverter output regulated to 60Hz +/-0.5Hz NUT INPUT Maximum input amps 12A Input cornection type NEMA 5-15P (space saving right-angle plug) Input cornection 4 (Fig. 1).8m 120V 15A BATTERY Full load runtime 3 min (750VA) Ball load runtime 10 min (375VA) DC system voltage 12VDC Typical battery illiespan 2 to 4 hours to reach 90% charge Battery recharge rate 2 to 4 hours to reach 90% charge Replacement Battery voltage regulation of description Automatic voltage regulation maintains 120V nominal over an input voltage range of 83V to 147V description Overvoltage conjulation of description Output voltage is reduced by 12% as line voltage increases to 128V or higher correction Drawnout correction Output voltage is boosted by 14% as line voltage decreases to 104V or lower	OUTPUT				
Output nominal voltage 120VAC Output voltage regulation Sine wave 120V +8% / -21% ((ine mode) / PWM sine wave 115V +/-5% ((battery mode)) Output frequency regulation LINE MODE: Passes line frequency of 60Hz +/-10% BATTERY MODE: Inverter output regulated to 60Hz +/-0.5Hz Outled quantity / type 12 NEMA 5-15R INPUT Maximum input amps 12A Input cornection type NEMA 5-15P (space saving right-angle plug) Input cord length 6 ft / 1.8m Recommended Electrical Service 120V 15A BATTERY Full load runtime 3 min (750VA) Bdf I cad runtime 10 min (375VA) DC system voltage 12VDC Typical battery lifespan 3 to 6 years, depending on usage Battery recharge rate 2 to 4 hours to reach 90% charge Replacement Battery cartridge RBC51 VOLTAGE REGULATIO** VOLTAGE REGULATIO** Voltage regulation correction Automatic voltage is reduced by 12% as line voltage increases to 128V or higher correction Brownout correction Output voltage is boosted by 14% as line voltage decreases to 104V or lower	Output VA	750			
voltage Cutput voltage regulation Sine wave 120V +8% / -21% (line mode) / PWM sine wave 115V +/-5% (battery mode) Output frequency regulation LINE MODE: Passes line frequency of 60Hz +/-10% BATTERY MODE: Inverter output regulated to 60Hz +/-0.5Hz Outbut frequency regulation 12 NEMA 5-15R INPUT WEMA 5-15P (space saving right-angle plug) Input connection type NEMA 5-15P (space saving right-angle plug) Input cord length 6 ft / 1.8m Recommended relectional Service 20V 15A BATTERY Full load runtime 3 min (750VA) BAT dear untime 10 min (375VA) DC system voltage 12VDC Typical battery lifespan 2 to 4 hours to reach 90% charge Battery recharge rate 2 to 4 hours to reach 90% charge Replacement Battery arridge RBCS1 VOLTAGE REGULATION Voltage regulation Voltage regulation Automatic voltage is reduced by 12% as line voltage increases to 128V or higher Brownout correction Output voltage is boosted by 14% as line voltage decreases to 104V or lower	Output watts	450			
regulation LINE MODE: Passes line frequency of 60Hz +/-10% BATTERY MODE: Inverter output regulated to 60Hz +/-0.5Hz Outlet quantity / type 12 NEMA 5-15R INPUT Maximum input amps 12A Input connection type NEMA 5-15P (space saving right-angle plug) Input cord length 6 ft / 1.8m Recommended Electrical Service 120V 15A BATTERY Full load runtime 3 min (750VA) Half load runtime 10 min (375VA) DC system voltage 12VDC Typical battery lifespan 3 to 6 years, depending on usage Battery recharge rate 2 to 4 hours to reach 90% charge Replacement Battery Cartridge RBC51 VOLTAGE REGULATION Automatic voltage regulation maintains 120V nominal over an input voltage range of 83V to 147V description Overvoltage correction Output voltage is reduced by 12% as line voltage increases to 128V or higher Brownout correction Output voltage is boosted by 14% as line voltage decreases to 104V or lower		120VAC			
regulation Outlet quantity / type 12 NEMA 5-15R INPUT Maximum Input amps 12A Input connection type NEMA 5-15P (space saving right-angle plug) Input cord length 6 ft / 1.8m Recommended Electrical Service 120V 15A Input a runtime 3 min (750VA) Input load runtime 10 min (375VA) DC system voltage 12VDC Itries pan 3 to 6 years, depending on usage Illies pan 8 Estery recharge rate 2 to 4 hours to reach 90% charge Replacement Battery Cartridge RBC51 VOLTAGE REGULATION Voltage regulation Automatic voltage regulation maintains 120V nominal over an input voltage range of 83V to 147V Covervoltage 0 utput voltage is reduced by 12% as line voltage decreases to 128V or higher Input cornection Coupt voltage is boosted by 14% as line voltage decreases to 104V or lower Input cornection Supple voltage decreases to 104V or lower Input cornection Coupt voltage is boosted by 14% as line voltage decreases to 104V or lower Input cornection Supple voltage is boosted by 14% as line voltage decreases to 104V or lower Input cornection Coupt voltage is boosted by 14% as line voltage decreases to 104V or lower Input cornection Coupt voltage is boosted by 14% as line voltage decreases to 104V or lower Input cornection Coupt voltage is boosted by 14% as line voltage decreases to 104V or lower Input cornection Coupt voltage is boosted by 14% as line voltage decreases to 104V or lower Input cornection Coupt voltage is boosted by 14% as line voltage decreases to 104V or lower Input cornection Coupt voltage is boosted by 14% as line voltage decreases to 104V or lower Input cornection Coupt voltage is boosted by 14% as line voltage decreases to 104V or lower Input cornection Coupt voltage is boosted by 14% as line voltage decreases to 104V or lower Input cornection Coupt voltage is boosted by 14% as line voltage is boosted voltage is boosted by 14% as line voltage is boosted voltage is boosted by 14% as line voltage is boosted voltage is boo		Sine wave 120V +8% / -21% (line mode) / PWM sine wave 115V +/-5% (battery mode)			
INPUT Maximum input amps 12A Input connection type NEMA 5-15P (space saving right-angle plug) Input cord length 6 ft / 1.8m Recommended Electrical Service 120V 15A BATTERY Full load runtime 3 min (750VA) Half load runtime 10 min (375VA) DC system voltage 12VDC Typical battery lifespan 3 to 6 years, depending on usage Battery recharge rate 2 to 4 hours to reach 90% charge Replacement Battery Cartridge RBC51 VOLTAGE REGULATION Voltage regulation scerefulation Automatic voltage regulation maintains 120V nominal over an input voltage range of 83V to 147V sescription Overvoltage correction Output voltage is reduced by 12% as line voltage increases to 128V or higher Brownout correction Output voltage is boosted by 14% as line voltage decreases to 104V or lower LEDS ALARMS & SWITCH		LINE MODE: Passes line frequency of 60Hz +/-10% BATTERY MODE: Inverter output regulated to 60Hz +/-0.5Hz			
Maximum input amps 12A Input connection type NEMA 5-15P (space saving right-angle plug) Input cord length 6 ft / 1.8m Recommended Electrical Service 120V 15A BATTERY Full load runtime 3 min (750VA) Half load runtime 10 min (375VA) DC system voltage 12VDC Typical battery lifespan 3 to 6 years, depending on usage Battery recharge rate 2 to 4 hours to reach 90% charge Replacement Battery artridge RBC51 VOLTAGE REGULATION Automatic voltage regulation maintains 120V nominal over an input voltage range of 83V to 147V Overvoltage correction Output voltage is reduced by 12% as line voltage increases to 128V or higher Brownout correction Output voltage is boosted by 14% as line voltage decreases to 104V or lower LEDS ALARMS & SWITCHES	Outlet quantity / type	12 NEMA 5-15R			
Input connection type Input cord length 6 ft / 1.8m Recommended Electrical Service BATTERY Full load runtime 10 min (375VA) DC system voltage 12VDC Typical battery lifespan Recolatery as Recolatery Replacement Battery Replacement Battery Toltage regulation Rescription Automatic voltage regulation maintains 120V nominal over an input voltage range of 83V to 147V Covervoltage correction Dutput voltage is boosted by 14% as line voltage decreases to 104V or lower LEDS ALARMS & SWITCHES	INPUT				
Input cord length 6 ft / 1.8m Recommended Electrical Service 120V 15A BATTERY Full load runtime 3 min (750VA) Half load runtime 10 min (375VA) DC system voltage 12VDC Typical battery lifespan 3 to 6 years, depending on usage lifespan 2 to 4 hours to reach 90% charge Replacement Battery RBC51 VOLTAGE REGULATION Voltage regulation description Automatic voltage regulation maintains 120V nominal over an input voltage range of 83V to 147V description Output voltage is reduced by 12% as line voltage decreases to 128V or higher correction Output voltage is boosted by 14% as line voltage decreases to 104V or lower LEDS ALARMS & SWITCHES	Maximum input amps	12A			
Recommended Electrical Service 120V 15A BATTERY Full load runtime 3 min (750VA) Half load runtime 10 min (375VA) DC system voltage 12VDC Typical battery lifespan 3 to 6 years, depending on usage lifespan 2 to 4 hours to reach 90% charge Replacement Battery Cartridge RBC51 VOLTAGE REGULATION Voltage regulation description Automatic voltage regulation maintains 120V nominal over an input voltage range of 83V to 147V description Overvoltage Output voltage is reduced by 12% as line voltage increases to 128V or higher or higher correction Output voltage is boosted by 14% as line voltage decreases to 104V or lower LEDS ALARMS & SWITCHES	Input connection type	NEMA 5-15P (space saving right-angle plug)			
Electrical Service BATTERY Full load runtime 3 min (750VA) Half load runtime 10 min (375VA) DC system voltage 12VDC Typical battery lifespan 3 to 6 years, depending on usage lattery recharge rate 2 to 4 hours to reach 90% charge Replacement Battery Automatic voltage regulation maintains 120V nominal over an input voltage range of 83V to 147V description 0 cutput voltage is reduced by 12% as line voltage increases to 128V or higher correction 0 cutput voltage is boosted by 14% as line voltage decreases to 104V or lower LEDS ALARMS & SWITCHES	Input cord length	6 ft / 1.8m			
Full load runtime 3 min (750VA) Half load runtime 10 min (375VA) DC system voltage 12VDC Typical battery lifespan 3 to 6 years, depending on usage lifespan 2 to 4 hours to reach 90% charge Replacement Battery cartridge RBC51 VOLTAGE REGULATION Voltage regulation description Automatic voltage regulation maintains 120V nominal over an input voltage range of 83V to 147V overvoltage correction Output voltage is reduced by 12% as line voltage decreases to 128V or higher lifespan as line voltage decreases to 104V or lower lifespan as line voltage decreases to 104V or lower lifespan as line voltage decreases to 104V or lower lifespan as line voltage decreases to 104V or lower lifespan as line voltage decreases to 104V or lower lifespan as line voltage decreases to 104V or lower lifespan as line voltage decreases to 104V or lower lifespan as line voltage decreases to 104V or lower lifespan as line voltage decreases to 104V or lower lifespan as line voltage decreases to 104V or lower lifespan as line voltage decreases to 104V or lower lifespan as line voltage lifespan as line voltage decreases to 104V or lower lifespan as line voltage lifespan as line voltage decreases to 104V or lower lifespan as line voltage lifespan as line voltage lifespan as lifespan as line voltage decreases to 104V or lower lifespan as lifespan a		120V 15A			
Half load runtime 10 min (375VA) DC system voltage 12VDC Typical battery lifespan 3 to 6 years, depending on usage lifespan 2 to 4 hours to reach 90% charge Replacement Battery Cartridge RBC51 VOLTAGE REGULATION Voltage regulation description Automatic voltage regulation maintains 120V nominal over an input voltage range of 83V to 147V overvoltage correction Output voltage is reduced by 12% as line voltage increases to 128V or higher lifespan as line voltage decreases to 104V or lower lifespan as line voltage decreases to 104V or lower lifespan as line voltage decreases to 104V or lower lifespan as line voltage decreases to 104V or lower lifespan as line voltage decreases to 104V or lower lifespan as line voltage decreases to 104V or lower lifespan as line voltage decreases to 104V or lower lifespan as line voltage decreases to 104V or lower lifespan as line voltage decreases to 104V or lower lifespan as line voltage decreases to 104V or lower lifespan as lif	BATTERY				
DC system voltage Typical battery lifespan Battery recharge rate 2 to 4 hours to reach 90% charge Replacement Battery Cartridge VOLTAGE REGULATION Voltage regulation description Automatic voltage regulation maintains 120V nominal over an input voltage range of 83V to 147V description Overvoltage correction Output voltage is reduced by 12% as line voltage increases to 128V or higher Dutput voltage is boosted by 14% as line voltage decreases to 104V or lower LEDS ALARMS & SWITCHES	Full load runtime	3 min (750VA)			
Typical battery lifespan 3 to 6 years, depending on usage Battery recharge rate 2 to 4 hours to reach 90% charge Replacement Battery Cartridge RBC51 VOLTAGE REGULATION Voltage regulation description Automatic voltage regulation maintains 120V nominal over an input voltage range of 83V to 147V Overvoltage correction Output voltage is reduced by 12% as line voltage increases to 128V or higher Dutput voltage is boosted by 14% as line voltage decreases to 104V or lower LEDS ALARMS & SWITCHES	Half load runtime	10 min (375VA)			
Battery recharge rate 2 to 4 hours to reach 90% charge Replacement Battery Cartridge RBC51 VOLTAGE REGULATION Voltage regulation description Automatic voltage regulation maintains 120V nominal over an input voltage range of 83V to 147V Overvoltage correction Output voltage is reduced by 12% as line voltage increases to 128V or higher LEDS ALARMS & SWITCHES	DC system voltage	12VDC			
Replacement Battery Cartridge VOLTAGE REGULATION Voltage regulation description Automatic voltage regulation maintains 120V nominal over an input voltage range of 83V to 147V description Overvoltage correction Output voltage is reduced by 12% as line voltage increases to 128V or higher Brownout correction Output voltage is boosted by 14% as line voltage decreases to 104V or lower LEDS ALARMS & SWITCHES		3 to 6 years, depending on usage			
VOLTAGE REGULATION Voltage regulation description Automatic voltage regulation maintains 120V nominal over an input voltage range of 83V to 147V description Overvoltage correction Output voltage is reduced by 12% as line voltage increases to 128V or higher Brownout correction Output voltage is boosted by 14% as line voltage decreases to 104V or lower LEDS ALARMS & SWITCHES	Battery recharge rate	2 to 4 hours to reach 90% charge			
Voltage regulation description Automatic voltage regulation maintains 120V nominal over an input voltage range of 83V to 147V description Overvoltage correction Output voltage is reduced by 12% as line voltage increases to 128V or higher Dutput voltage is boosted by 14% as line voltage decreases to 104V or lower LEDS ALARMS & SWITCHES		RBC51			
Overvoltage correction Output voltage is reduced by 12% as line voltage increases to 128V or higher Brownout correction Output voltage is boosted by 14% as line voltage decreases to 104V or lower LEDS ALARMS & SWITCHES	VOLTAGE REGULATIO	N .			
Brownout correction Output voltage is boosted by 14% as line voltage decreases to 104V or lower LEDS ALARMS & SWITCHES		Automatic voltage regulation maintains 120V nominal over an input voltage range of 83V to 147V			
LEDS ALARMS & SWITCHES		Output voltage is reduced by 12% as line voltage increases to 128V or higher			
	Brownout correction	Output voltage is boosted by 14% as line voltage decreases to 104V or lower			
Front panel LEDs 2 LEDs indicate line power, battery power status	LEDS ALARMS & SWIT	CHES			
	Front panel LEDs	2 LEDs indicate line power, battery power status			

Alarms	Audible alarm beeps at regular intervals to indicate battery backup operation. Alarm also sounds during self-test
Cuitabaa	operation. Alarm can be disabled altogether via PowerAlert software
Switches	Combination power off / on / self-test push button switch
AC surge suppression	
	400 joules
Dataline suppression	Tel/DSL
EMI / RFI AC noise suppression	Yes
PHYSICAL	
Shipping weight (lbs)	16.3
Shipping weight (kg)	7.4
Shipping Dimensions (HWD/in)	5.5 x 14.5 x 9.75
Shipping Dimensions (HWD/cm)	14 x 36.8 x 24.8
Unit weight (lbs)	15.3
Unit weight (kg)	6.9
Unit Dimensions (HWD/in)	4 x 12 x 7
Unit Dimensions (HWD/cm)	10.2 x 30.5 x 17.8
Material of construction	ABS
Form factors supported	Ultra-compact
Battery Access	Hot-swappable batteries are accessible via battery door
ENVIRONMENTAL	
Operating Temperature	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius
Storage Temperature	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius
Relative Humidity	0 to 95%, non-condensing
COMMUNICATIONS	
Network monitoring port	USB (HID)
Software and cabling included	Includes USB cable, PowerAlert UPS monitoring software CD-ROM, RJ-11 phone cable
WatchDog compatibility	Yes, compatible with Tripp Lite's Watchdog system service to restore operation to locked equipment through soft reboot of application / OS or hard power off/on reboot of connected equipment - ideal for unattended kiosk applications
LINE / BATTERY TRANS	SFER
Transfer time from line power to battery mode	2 to 4 milliseconds
Low voltage transfer to battery power	Switches to battery power as line voltage drops to 83V or lower / Resets to AC mode as line voltage increases to 87V or higher
High voltage transfer to battery power	Switches to battery power as line voltage increases to 147V or higher / Resets to line power as line voltage drops to 143V or less
SPECIAL FEATURES	
Cold Start	Yes, inverter can be "cold started" to enable temporary AC output during a power failure
CERTIFICATIONS	

Certifications	Tested to UL1778 (USA), CSA C22.2 No. 107.3 (Canada), NOM (Mexico), Class B (emissions), FCC Part 68 and Industry Canada (telecommunications)
WARRANTY	
Product warranty	2 years
Optional coverage	Optional 3- and 5-year on-site or factory warranties available for select opportunities. Contact Tripp Lite for more information.

Related Items

Audio Cables		
CT120	Instant-Read- AC Outlet Circuit Tester	Qty: [optional]
Extended Warranties		
WEXT3-INTERNET	3-Year Extended Warranty - For Internet Office Models	Qty: [optional]
WEXT5-INTERNET	5-Year Extended Warranty - For Internet Office Models	Qty: [optional]
Software		
WATCHDOGSW	WatchDog Service Monitoring / Reboot Software	Qty: [optional]
Surge Protectors		
DTEL2	Network Surge Suppressor - Essential protection for data and communication lines	Qty: [optional]
DNET1	Network Surge Suppressor - Essential protection for data and communication lines	Qty: [optional]
DCATV	Network Surge Suppressor - Essential protection for TV/VCR coaxial lines	Qty: [optional]
USB Cables & Adapters		
U005-10I	USB Gold Extension cable - USB "A" Right Angle Male to USB "A" Female - 10"	Qty: [optional]
USB Hubs/Accessories		
U222-004-R	USB Hubs - 4-Port USB 2.0 Certified Ultra-Mini Hub	Qty: [optional]

©2009 Tripp Lite. All Rights Reserved.