

## Smart-UPS XL

### APC Smart-UPS XL 1000VA USB & Serial 120V



APC Smart-UPS XL, 800 Watts / 1000 VA, Input 120V / Output 120V, Interface Port DB-9 RS-232, SmartSlot, USB, Extended runtime model

**Includes:** CD with software, Smart UPS signalling RS-232 cable, USB cable, User Manual

**Standard Lead Time:** Usually in Stock

## SUA1000XL Features

|                  |  |
|------------------|--|
| USB Connectivity | Provides management of the UPS via a USB port (not available on all models). |
|------------------|--|

## Smart-UPS XL Features & Benefits

### Availability

|   |  |
|---|--|
| Scalable runtime                                  | Allows additional run time to be quickly added as needed.  |
| Boost and Trim Automatic Voltage Regulation (AVR) | Gives higher application availability by correcting low and high voltage conditions without using the battery. |
| Power conditioning                                | Protects connected loads from surges, spikes, lightning, and other power disturbances.                         |
| Temperature-compensated battery charging          | Prolongs battery life by regulating the charge voltage according to battery temperature.                       |
| Intelligent Battery Management                    | Maximizes battery performance, life, and reliability through intelligent, precision charging.                  |
| Automatic restart of loads after UPS shutdown     | Automatically starts up the connected equipment upon the return of utility power.                              |
| Automatic self-test                               | Periodic battery self-test ensures early detection of a battery that needs to be replaced.                     |
| Cold-start capable                                | Provides temporary battery power when the utility power is out.  |
| Disconnected battery notification                 | Warns when a battery is not available to provide backup power.   |
| Generator Compatible                              | Ensures clean, uninterrupted power to protected equipment when generator power is used.                        |

### Manageability


|                                   |  |
|-----------------------------------|--|
| Network manageable SmartSlot      | Provides remote management of the UPS over the network. Customize UPS capabilities with management cards.    |
| Audible Alarms                    | Actively let you know if the unit is on battery, if the battery is low or if there is an overload condition. |
| LED status indicators             | Quickly understand unit and power status with visual indicators.   |
| Disconnected battery notification | Warns when a battery is not available to provide backup power.   |
| Serial Connectivity               | Provides management of the UPS via a serial port.  |
| InfraStruXure Manager Compatible  | Enables centralized management via the APC InfraStruXure® Manager.   |

### Serviceability


|                            |   |
|----------------------------|---|
| User-replaceable batteries | Increases availability by allowing a trained user to perform upgrades and replacements of the batteries reducing Mean Time to Repair (MTTR) |
| Hot-swappable              | Ensures clean, uninterrupted power to protected equipment while batteries   |

|                                    |  |
|------------------------------------|--|
| batteries                          | are being replaced   |
| Predictive failure notification    | Provides early-warning fault analysis ensuring proactive component replacement.  |
| Resettable circuit breakers        | Enables a quick recovery from overload events.   |
| <b>Adaptability</b>                |  |
| Plug-and-Play external batteries   | Ensures clean, uninterrupted power to the loads when adding extra runtime to the UPS.  |
| Adjustable voltage-transfer points | Maximizes useful battery life by widening the input voltage window or tightening the output voltage regulation.  |
| Adjustable voltage sensitivity     | Provides the ability to adapt the UPS for optimal performance in specific power environments or generator applications.  |
| <b>Safety</b>                      |  |
| Safety-agency approved             | Ensures the product has been tested and approved to work safely with the connected service provider equipment and within the specified environment. UL, FCC, CE, C-Tick approvals. |

# Output

|                                  |  |
|----------------------------------|--|
| Output Power Capacity            | 800 Watts / 1000 VA  |
| Max Configurable Power           | 800 Watts / 1000 VA  |
| Nominal Output Voltage           | 120V   |
| Output Voltage Distortion        | Less than 5% at full load  |
| Output Frequency (sync to mains) | 47 - 53 Hz for 50 Hz nominal, 57 - 63 Hz for 60 Hz nominal   |
| Crest Factor                     | up to 5 : 1  |
| Waveform Type                    | Sine wave  |
| Output Connections               | (8) NEMA 5-15R  |

# Input

|  |  |
|--|--|
| Nominal Input Voltage                              | 120V   |
| Input Frequency                                    | 50/60 Hz +/- 3 Hz (auto sensing)   |
| Input Connections                                  | NEMA 5-15P  |
| Cord Length  | 1.83 meters  |
| Input voltage range for main operations            | 82 - 144V  |
| Input voltage adjustable range for mains operation | 75 - 154V  |

# Batteries & Runtime

|                                  |  |
|----------------------------------|--|
| Battery Type                     | Maintenance-free sealed Lead-Acid battery with suspended electrolyte : leakproof |
| Typical recharge time            | 2 hour(s)  |
| Replacement Battery              | <a href="#">RBC7</a>   |
| RBC™ Quantity                    | 1  |
| Typical Backup Time at Half Load | 33.3 minutes (400 Watts)   |
| Typical Backup Time at Full Load | 9.6 minutes (800 Watts)  |

Runtime Chart

[Smart-UPS XL](#)

Extended Run Options

[APC Smart-UPS XL 1000VA USB & Serial 120V](#)

## Communications & Management

|   |  |
|---|--|
| Interface Port(s)                       | DB-9 RS-232,SmartSlot,USB  |
| Available SmartSlot™ Interface Quantity | 1  |
| Control panel                           | LED status display with load and battery bar-graphs and On Line : On Battery : Replace Battery : and Overload Indicators |
| Audible Alarm                           | Alarm when on battery : distinctive low battery alarm : configurable delays  |
| Emergency Power Off (EPO)               | Optional   |

## Surge Protection and Filtering

|                     |  |
|---------------------|--|
| Surge energy rating | 459 Joules   |
| Filtering           | Full time multi-pole noise filtering : 0.3% IEEE surge let-through : zero clamping response time : meets UL 1449 |

## Physical

|                  |           |
|------------------|-----------|
| Maximum Height   | 216.00 mm |
| Maximum Width    | 170.00 mm |
| Maximum Depth    | 439.00 mm |
| Net Weight       | 27.27 KG  |
| Shipping Weight  | 29.55 KG  |
| Shipping Height  | 387.00 mm |
| Shipping Width   | 320.00 mm |
| Shipping Depth   | 591.00 mm |
| Color            | Black     |
| Units per Pallet | 24.00     |

## Environmental

|                             |               |
|-----------------------------|---------------|
| Operating Environment       | 0 - 40 °C     |
| Operating Relative Humidity | 0%            |
| Operating Elevation         | 0-3000 meters |
| Storage Temperature         | -15 - 45 °C   |
| Storage Relative Humidity   | 0%            |

|   |                |
|---|----------------|
| Storage Elevation                             | 0-15000 meters |
| Audible noise at 1 meter from surface of unit | 42.00 dBA      |
| Online Thermal Dissipation                    | 120.00 BTU/hr  |

## Conformance

|                      |                                      |
|----------------------|--------------------------------------|
| Regulatory Approvals | BSMI,CSA,FCC Part 15 Class A,UL 1778 |
| Standard Warranty    | 2 years repair or replace            |
| ROHS/WEEE Compliance | RoHS 7b Exemption                    |

\*\*The time to recharge to 90% of full battery capacity following a discharge to shutdown using a load rated for 1/2 the full load rating of the UPS.