

Smart-UPS VT APC Smart-UPS VT 15kVA 208V w/2 Batt. Modules, Start-Up 5X8, Internal Maintenance Bypass



APC Smart-UPS VT, 12 kW / 15 kVA,Input 208V 3PH / Output 120V, 208V, 208V 3PH, Interface Port DB-9 RS-232, Smart-Slot

Includes: Battery modules ship installed, Bolt down brackets, CD with software, Installation guide, Power modules ship installed, Smart UPS signalling RS-232 cable, Start up included, User Manual, Web/SNMP Management Card

Smart-UPS VT Features & Benefits

| Availability | |
|---|---|
| Dual mains input | Increases availability by allowing the UPS to be connected to two separate power sources. |
| Scalable runtime | Allows additional run time to be quickly added as needed. |
| Hot-swappable | Ensures clean, uninterrupted power to protected equipment while batteries |
| batteries | are being replaced |
| - | Ensures clean, uninterrupted power to protected equipment when generator power is used. |
| Automatic internal bypass | Supplies utility power to the connected loads in the event of a UPS overload condition or fault. |
| Battery modules connected in parallel Serviceability | Delivers higher availability through redundant batteries. |
| User-replaceable batteries Battery replacement without tools | Increases availability by allowing a trained user to perform upgrades and replacements of the batteries reducing Mean Time to Repair (MTTR) Allows quick, easy battery replacement. |
| Automatic self-test | Periodic battery self-test ensures early detection of a battery that needs to be replaced. |
| Shippable with modules installed | Enables pre-installation UPS staging and testing and faster installation. |
| Modular design | Provides fast serviceability and reduced maintenance requirements via self- diagnosing, field-replaceable modules. |
| Manageability | |
| Network manageable | Provides remote management of the UPS over the network. |
| InfraStruXure | Enables centralized management via the APC InfraStruXure® Manager. |
| Manager Compatible | |
| LCD display | Alpha-Numeric Display which displays system parameters and alarms. |
| Audible Alarms | Provides notification of changing utility power and UPS conditions. |
| Programmable frequency | Ensures compatibility with different input frequencies. |
| LED status indicators SmartSlot | Quickly understand unit and power status with visual indicators. Customize UPS capabilities with management cards. |
| Total Cost of Ownership | |
| Input power factor | Minimizes installation costs by enabling the use of smaller generators and |
| correction | cabling. |
| Temperature- compensated battery charging | Prolongs battery life by regulating the charge voltage according to battery temperature. |
| Manual maintenance bypass | Reduces installation costs by eliminating the need for an external mechanical bypass. |
| Intelligent Battery Management | Maximizes battery performance, life, and reliability through intelligent, precision charging. |
| Protection | |
| regulation | Gives higher application availability by correcting poor frequency and voltage conditions without using the battery. |
| Safety-agency | Ensures the product has been tested and approved to work safely with the |

| approved | connected service provider equipment and within the specified environment. UL, FCC, CE, C-Tick approvals. |
|--------------------|--|
| Cold-start capable | Provides temporary battery power when the utility power is out. |

Output

| - | |
|----------------------------------|---|
| Output Power Capacity | 12 kW / 15 kVA |
| Max Configurable Power | 12 kW / 15 kVA |
| Nominal Output Voltage | 120V,208V,208V 3PH |
| Output Voltage Note | Configurable for 208 and 220V - 3 Phase |
| Efficiency at Full Load | 93% |
| Output Voltage Distortion | Less than 5% at full load |
| Output Frequency (sync to mains) | 57 - 63 Hz for 60 Hz nominal |
| Crest Factor | Unlimited |
| Waveform Type | Sine wave |
| Output Connections | (1) Hard Wire 5-wire $(3PH + N + G)$ |
| | (1) Screw Terminals |
| Bypass | Built-in Maintenance Bypass, Built-in Static Bypass |
| | |

Input

| Nominal Input Voltage | 208V 3PH |
|---|----------------------------------|
| Input Frequency | 40 - 70 Hz |
| Input Connections | Hard Wire 5-wire $(3PH + N + G)$ |
| Input voltage range for main operations | 165 - 240V |
| Other Input Voltages | 220 |
| Maximum Input Current | 40A |
| Input Breaker Capacity | 60A |

Batteries & Runtime

| Battery Type | VRLA |
|-------------------------------------|----------------------------|
| Included Battery Modules | 2 |
| Typical recharge time | 5 hour(s) |
| Replacement Battery | <u>SYBT4</u> |
| RBC [™] Quantity | 2 |
| Typical Backup Time at Half Load | 28.1 minutes (6000 Watts) |
| Typical Backup Time at Full Load | 10.0 minutes (12000 Watts) |
| Runtime Chart | Smart-UPS VT |

Communications & Management

| Interface Port(s) | DB-9 RS-232,Smart-Slot |
|--|--|
| Pre-Installed SmartSlot [™] Cards | <u>AP9619</u> |
| Control panel | Multi-function LCD status and control console |
| Audible Alarm | Audible and visible alarms : configurable delays |
| Emergency Power Off (EPO) | Yes |

Physical

| Maximum Height | 1499.00 mm |
|------------------|------------|
| Maximum Width | 356.00 mm |
| Maximum Depth | 925.00 mm |
| Net Weight | 396.82 KG |
| Shipping Weight | 428.18 KG |
| Shipping Height | 1643.00 mm |
| Shipping Width | 650.00 mm |
| Shipping Depth | 1062.00 mm |
| Color | Black |
| Units per Pallet | 1.00 |
| | |

Environmental

| Operating Environment | 0 - 40 °C |
|---|----------------|
| Operating Relative Humidity | 0% |
| Operating Elevation | 0-999.9 meters |
| Storage Temperature | -50 - 40 °C |
| Storage Relative Humidity | 0% |
| Storage Elevation | 0-15000 meters |
| Audible noise at 1 meter from surface of unit | 54.00 dBA |
| Online Thermal Dissipation | 3276.00 BTU/hr |
| Protection Class | NEMA 1 |

Conformance

| Regulatory Approvals | cUL Recognized,ISO 14001,ISO 9001,UL 1778 |
|----------------------|--|
| Standard Warranty | 1 year repair or replace, Start-Up Service |

**The time to recharge to 90% of full battery capacity following a discharge to shutdown using a load rated for 1/2 the full load rating of the UPS.