semiconductors :: product :: Bridge Rectifiers (Power)

## **Product:** Bridge Rectifiers (Power)

Bridge Rectifiers are key devices in many applications where a rectifier signal is required as Input voltage. Linear Power Supplies, SMPS, Battery Chargers, Electronic Ballast... are some applications where they are used.

Manufactured using HYPERECTIFIER© technology, we offer these devices in several different packages: SMD, Dual In Line, Round, In Line and Square Power.


Product	Family	$I_{F(AV)}(A)$	$I_{FSM}(A)$	$V_{RRM}(V)$	$V_F(V)$	OUTLINE
FB1510L-B500/440-15L	FB15-L	15.0	300	1000	1.1	Power - Wire leads







## 15 Amp. Glass Pasivated Bridge Rectifiers



## Maximum Ratings, according to IEC publication No. 134

	1	FB1500	FB1501	FB1502	FB1504	FB1506	FB1508	FB1510	
	2	FB1500L	FB1501L	FB1502L	FB1504L	FB1506L	FB1508L	FB1510L	
	1	FB1500M	FB1501M	FB1502M	FB1504M	FB1506M	FB1508M	FB1510M	
$V_{RRM}$	Peak Recurrent Reverse Voltage (V)	50	100	200	400	600	800	1000	
V <sub>RMS</sub>	Maximum RMS Voltage (V)	35	70	140	280	420	560	700	
$V_R$	Recommended Input Voltage (V)	20	40	80	125	250	380	500	
I <sub>F (AV)</sub>	Max. Forward Current R-load: At T case = 55 °C At T case = 90 °C		15 A 10 A						
With Al Square Chassis (200 cm <sup>2</sup> x 3 mm.)  Tamb = 45 °C		8 A							
I <sub>FRM</sub>	I <sub>FRM</sub> Recurrent Peak Forward Current		60 A						
I <sub>FSM</sub>	I <sub>FSM</sub> 10 ms. Peak Forward Current		300 A						
I <sup>2</sup> t	<sup>2</sup> t I <sup>2</sup> t value for fusing (t = 10ms)		450 A <sup>2</sup> sec						
Tj	T <sub>j</sub> Operating junction temperature range		– 55 to + 150 °C						
T <sub>stg</sub> Storage temperature range		– 55 to + 150 °C							

## **Electrical Characteristics at Tamb = 25 °C**

V <sub>F</sub>	Max. forward voltage drop per element at $I_F = 7.5 \text{ A}$	1.1 V			
I <sub>R</sub>	Maximum reverse current per element at V <sub>RRM</sub> d.c.	5 μΑ			
R <sub>thj-C</sub>	Typical thermal resistance junction to case	1.4 °C/W			
	Isolation voltage from case to leads	2500 Vac			