

## Passive Voltage Probes

P3010 • P6101B • P6109B • P6111B • P6112 • P6114B • P6117

### Characteristics

Type	Attenuation	Bandwidth Megahertz (MHz)	Comp. Range Picofarads (pF)	System Input Resistance (MΩ)	Typical Input C Picofarads (pF)	Input RMS CATI CATII (Volts)	Readout	Scope/Product
P6101B	1X	15	NA	1	100	300 V <sub>RMS</sub> CAT I		All Scopes
P6109B	10X	100	15 to 35	10	13	400 V <sub>RMS</sub> CAT I 300 V <sub>RMS</sub> CAT II	X	2211, 2221, 2224, 2230, 2232, 2235A, 2236A, 2245A, 2246A, 2247A, 2252, TAS455, TAS465, TAS475, TDS310, TDS320, TDS340, TDS340A
P6111B	10X	200	15 to 35	10	14	400 V <sub>RMS</sub> CAT I 300 V <sub>RMS</sub> CAT II	X	TAS485, TDS350, TDS360
P6112	10X	100	15 to 35	10	13.3	400 V <sub>RMS</sub> CAT I 300 V <sub>RMS</sub> CAT II		TDS200



B-Series Family Photo.

#### Product Information

[Introduction](#)

► [Characteristics/Specs](#)

[Ordering Information](#)

#### Pricing Information

[Check List Price](#)

[Request a Quote](#)

#### Additional Resources

[Find an Authorized Distributor](#)

Search

#### Product Portfolio

- [Oscilloscope Probes](#)
- [Logic Analyzer Probes/ P6400](#)
- [Logic Analyzer Probes/ P68/6900](#)
- [Optical Products](#)
- [Application Software](#)
- [Request a Catalog](#)
- [Product Finder](#)

#### Resources

- [Technical Information](#)
- [Manuals](#)
- [Software & Drivers](#)
- [Service & Support](#)
- [E-Newsletters](#)

#### What's New

- [Promotions](#)
- [News](#)
- [Events](#)

P6114B	10X	400	10 to 35	10	14.1	400 V <sub>RMS</sub> CAT I 300 V <sub>RMS</sub> CAT II	X	TDS380
P6117	10X	200	15 to 35	10	13.3	400 V <sub>RMS</sub> CAT I 300 V <sub>RMS</sub> CAT II		THS700
P3010	10X	100	15 to 35	10	13	400 V <sub>RMS</sub> CAT I 300 V <sub>RMS</sub> CAT II	X	TDS3012, TDS3012B, TDS3014, TDS3014B

[▲ back to top](#)

[Introduction](#)

**► Characteristics/Specs**

[Ordering Information](#)

[Check List Price](#)

[Request a Quote](#)

[Find an Authorized Distributor](#)



Product(s) are manufactured in ISO registered facilities.

60W-15106-1A, 06-JAN-2005



[Have an Account Manager Contact Me](#)



[Request a Demo](#)



[Email This Page](#)



[Printable Page](#)

**Tektronix Site**

[Home](#) | [Products](#) | [Support](#) | [Buy](#) | [Contact Us](#) | [Investors](#) | [Careers](#) | [International](#) | [myTek](#)

[Sitemap](#) | [© Copyright Tektronix, Inc.](#) | [Privacy Statement](#)