

## Current Sense Xfmr-SMD Type: 0-10A, 250kHz+

Designed to monitor current at 250kHz and above. These transformers have a primary current rating of 10 Amps max.

Part No.	Turn Ratio N1:N2	Sec Inductance uH Min.	Sec DCR mΩ Max
<a href="#"><u>CSE5-100201</u></a>	1:20	80	550
<a href="#"><u>CSE5-100301</u></a>	1:30	180	870
<a href="#"><u>CSE5-100401</u></a>	1:40	320	1140
<a href="#"><u>CSE5-100501</u></a>	1:50	500	1500
<a href="#"><u>CSE5-100601</u></a>	1:60	720	1750
<a href="#"><u>CSE5-100701</u></a>	1:70	980	4750
<a href="#"><u>CSE5-101001</u></a>	1:100	2000	5500
<a href="#"><u>CSE5-101251</u></a>	1:125	3000	6500

