

# POWER TRANSFORMER CHASSIS MOUNT: TOROIDAL WORLD SERIES

# **VPT230-2170**

# Electrical Specifications (@25C)

1. Maximum Power: 500VA

2. Input Voltage: Series: 230VAC, 50/60Hz

Parallel: 115VAC, 50/60Hz

3. Output Voltage: Series: 230VAC CT @ 2.17A

Parallel: 115.0VAC @ 4.34A

4. Voltage Regulation: 5% TYP from full load to no load

5. Temperature Rise: 50°C TYP

6. Hipot: 4000VAC, Primary to Secondary

7. Efficiency: 94% TYP. @ full load

#### Construction:

The toroidal construction inherently helps reduce stray fields, increases efficiency and minimizes size compared to traditional EI transformers. Built with Class B (130°) insulation system.

#### Safety:

World Series Transformers are designed and manufactured to meet most International Safety agency standards.

#### Agency File:

UL: File E122529, UL 506

CE: EN 61558-1:2005, EN 61558-2-6:1995, Low Voltage Directive (LVD) EN 6-000-6-6:2001+A11:2004, EN 55014-1:2000+A1:2001+A2:2002, EN 6100-6-1:2001, EN 55014-2:1997+A1:2001, Electromagnetic Compatibility (EMC)



Dimensions (mm):

Н	I.D.	O.D.
60.0	46.0	140.0

Weight: 4.2Kg

### Mounting:

Transformer is provided with one metal mounting plate, two rubber pads, M8 x 70mm bolt, nut, spring and flat washer.

## **Connections:**

Transformer is provided with 12" (305mm) long, 0.50" (12.7mm) stripped and tinned, stranded UL 1015 lead wire.

Input1: Series - BLUE and BROWN, Jumper GRAY to VIOLET

Parallel - BLUE and BROWN, Jumper BLUE to VIOLET, GRAY to BROWN

Output<sup>1</sup>: Series – BLACK and YELLOW, Jumper RED to ORANGE


Parallel - BLACK and YELLOW, Jumper BLACK to ORANGE, RED to YELLOW


**RoHS Compliance:** Product meets the requirements of 2002/95/EC, known as the RoHS initiative.

\* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.

Web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757 22520B Temescal Canyon Road Corona, California 92883







**RUBBER** 

PAD

NUT

**SPRING** 

WASHER

<sup>&</sup>lt;sup>1</sup> Primary and secondary windings are designed to be connected in series or parallel. Windings are not intended to be used independently.