Marsh Bellofram Group of Companies





Search

< Marsh Bellofram Group of Companies < Automatic Timing & Controls < Timer < 422A Series 422A Series Multi-Range Repeat Cycle Timer Purchase Details: Six Selectable Ranges: 1 and 10 SEC/MIN/HRS; 5 and 50 SEC/MIN/ HRS Individually adjustable ON-time and OFF-time Product C Cycle can begin with relay energized or de-energized • Both Repeat Cycle and Single Cycle operation available Sales C Cycle progress indication DPDT Relay Output Specificat Power: 24VDC, 24 to 240VAC Standard 1/8 DIN Housing Can be panel mounted Range Contact Rating Product Detail: The **422A FLIP-FLOP** is available with *Repeat Cycle* operation. During Repeat Cycle operation the 422A cycles ON and OFF repeatedly, allowing periodic cycling of a load. Two knobs are available to individually adjust the Life ON-time and the OFF-time. The 422A can be ordered with either the relay being energized during the first timing period or de-energized during the first timing period. Contact The 422A FLIP-FLOP is also available with *Single Cycle* operation. With Material Single Cycle operation, the 422A will cycle ON and OFF one time. This is Temperature commonly referred to as "one-shot" operation. The 422A can be ordered Rating with the relay being energized during the first timing period or de-energized during the first timing period. There are six selectable timing ranges available for the ON-time period and Noise 6 selectable ranges for the OFF-time period. These ranges can be ordered as Immunity either 1 and 10 SEC/MIN/HRS or 5 and 50 SEC/MIN/HRS. Having these ranges individually selectable for ON-time and OFF-time allows for a load to be energized for a brief time over a cycle that can last up to 50 hours. This is ideal for lubrication or other maintenance functions that must occur each

The 422A's 1/8 DIN housing is compact, and designed for panel mounting. The timer is mounted in an 8-pin round (octal) socket. The front of the 422A

Contact:	
Contact	Technical Contact
tions:	
	422A100 ¹ or 10 SEC/ MIN/HRS

5 or 50 SEC/ 422A500 MIN/HRS Rated 10 AMPS resistive at 30 VDC or 250 VAC

(or less) 1/8 HP @ 120 VAC 1/4 HP @ 240 VAC

240 VA @ 240 VAC

10 million operations with no load 100,000 operations with: 10 AMPS at 30 VDC (or less)

Silver Cadmium Oxide

0° to 140°F (-18°C to 60°C)

Showering ARC per NEMA ICS 2-230. In addition, the 422A will withstand a voltage surge of 4500 volts for 50 µsec. without damage.

Plug-in octal base

Surface mounting socket



Downloadable Files:

422A Series

shift or day during a plant operation.

features 2 knobs. One knob is used to set the On-time and the other knob is used to set the Off-time for the timer's cycle.

The timing range for the On-time and Off-time can be individually set. The range select switches are located on the side of the housing, so that when panel mounted, these switches are not accessible to the operator. This tamper proof feature prevents unauthorized or hazardous changes to the timing range from being made.

The output of the 422A is a DPDT mechanical relay which is rated for 10 Amps at 30 VDC and 240 VAC. The 422A can be ordered with this output being energized during the first timing period, or de-energized during the first timing period.

A single Flip-Flop Timer can be powered using 24-240 VAC or 24 VDC power, greatly simplifying ordering and inventory management of replacement units. The 422A has individual LED indicators for ON-time and Off-time. These LED's provide a unique and effective method of cycle progress indication. Off before timing, the LED's blink at an ever increasing rate as the cycle progresses: once every 3 1/2 seconds during the first 10% of the cycle, twice during the second 10%, and so on until the timing cycle is complete. (In the 1, 5, 10 and 50 second ranges, the LED is Off before timing and steady On during the timing cycle).

Part Numbers:

4						
					422A	Create Part Number >>>>
					Range	
					c/Min/Hrs)	Six dial-selected ranges (1 or 10 Sec
				100		
				500	c/Min/Hrs)	Six dial-selected ranges (5 or 50 Se
				quency	tage & Free	Vol
			F	24 VDC	OHz) and 2	24 to 240 VAC (50/6
			Ε	2 VDC	1	
			nce	Seque		
		1	T2)	during	energized	OFF/ON (Relay
		3	T1)	during	energized	ON/OFF (Relay
		ype	le T	Сус		
	0	ycle	at Cy	Repe		
	5	ycle	le Cy	Sing		
	res	eatu	F			
Х	ner	d Tir	ndar	Sta		
К	cial	Spe				

DIN rail mounting Mounting socket Options Plug-in socket kit (8-pin) Panel mounting kit 8-pin panel socket w/rear facing terminals Universal power supply. Unit will accept power from 24 to 240 VAC, 50 or 60 Hz, (+10%, -20%) 24 VDC (+20%, -20%) Inrush - 1.5 Amps AC Power required Power - 1.2 watts Requirements Maximum ripple at 60 Hz - 5% Current DC required -50mA Power required - 1.2 Watts 2% of range, with the Minimum exception of 50 mSec on Setting the seconds range. Setting +/-5% of range Accuracy Varies as a function of temperature. Any voltage (constant temperature): $\pm 0.5\%^*$ Repeat Any voltage (32° F to 140° F): ± 1.5%* Accuracy Any voltage (0° F to 140° F): ± 2.0%* *Variation from average actual time 0 to 20 mSec power interruption: guaranteed no reset 20 to 65 mSec; Reset it may reset b (40 mSec typical reset)

Options:

Accessories]	Over 65 mSec c guaranteed to reset
8-Pin surface/DIN rail socket	0000-825-85-00	Weight	7 ounces
Hold down for above socket	0422-025-02-00	,	
Panel mounting kit consisting of gasket and 2 clamps	0328-260-02-00		
Plug-in socket kit (8-pin)	0319-261-45-00		
8-Pin panel socket w/rear facing terminals	600-3-0011		

• Bellofram Precision Controls • Marsh Instruments • BelGAS • Bellofram Diaphragm • Diversified Electronics • DigiTec Division • Thermo-Couple Products

422A Series



Multi-Range Repeat Cycle Timet Multi-Range Repeat Cycle The 420 Six Selectable P-1 april c**A**SUS

- 5 and 50 SEC/MIN/HRS
- Individually adjustable ON-time and OFF-time
- Cycle can begin with relay energized or de-energized
- Both Repeat Cycle and Single Cycle operation available
- Cycle progress indication
- DPDT Relay Output
- Relay rated 10 A @ 30 VDC, 240 VAC
- Power: 24 VDC, 24 to 240 VAC
- Standard 1/8 DIN Housing
- Can be panel mounted

\square 4.25 108 \bigcirc 3.88 98.5 <u>.32</u> 8.13 О 1.89 48 (OPTIONAL SOCKET) .813 PANEL 20.6 CUT-OUT 2.5 63.5 $\frac{1.7}{43}$

DIMENSIONS (INCHES/MILLIMETERS)

The 422A FLIP-FLOP is available with Repeat Cycle operation. During Repeat Cycle operation the 422A cycles ON and OFF repeatedly, allowing periodic cycling of a load. Two knobs are available to individually adjust the ONtime and the OFF-time. The 422A can be ordered with either the relay being energized during the first timing period or de-energized during the first timing period.

The 422A FLIP-FLOP is also available with Single Cycle operation. With Single Cycle operation, the 422A will cycle ON and OFF one time. This is commonly referred to as "one-shot" operation. The 422A can be ordered with the relay being energized during the first timing period or de-energized during the first timing period.

There are six selectable timing ranges available for the ON-time period and 6 selectable ranges for the OFF-time period. These ranges can be ordered as either 1 and 10 SEC/MIN/HRS or 5 and 50 SEC/MIN/HRS. Having these ranges individually selectable for ON-time and OFF-time allows for a load to be energized for a brief time over a cycle that can last up to 50 hours. This is ideal for lubrication or other maintenance functions that must occur each shift or day during a plant operation.


The 422A's 1/8 DIN housing is compact, and designed for panel mounting. The timer is mounted in an 8-pin round (octal) socket. The front of the 422A features 2 knobs. One knob is used to set the On-time and the other knob is used to set the Off-time for the timer's cycle.

> The timing range for the On-time and Off-time can be individually set. The range select switches are located on the side of the housing, so that when panel mounted, these switches are not accessible to the operator. This tamper proof feature prevents unauthorized or hazardous changes to the timing range from being made.

> The output of the 422A is a DPDT mechanical relay which is rated for 10 Amps at 30 VDC and 240 VAC. The 422A can be ordered with this output being energized during the first timing period, or de-energized during the first timing period.

A single Flip-Flop Timer can be powered using 24-240 VAC or 24 VDC power, greatly simplifying ordering and inventory management of replacement units.

The 422A has individual LED indicators for ON-time and Off-time. These LED's provide a unique and effective method of cycle progress indication. Off before timing, the LED's blink at an ever increasing rate as the cycle progresses: once every 3 1/2 seconds during the first 10% of the cycle, twice during the second 10%, and so on until the timing cycle is complete. (In the 1, 5, 10 and 50 second ranges, the LED is Off before timing and steady On during the timing cycle).




3.78

96

3.58

91



Repeat Cycle Timers // 422A Series

\\\SPECIF	ICATIONS	5		
DANICE	422A100	1 or 10 SEC/MIN/HRS		
RANGE	422A500	5 or 50 SEC/MIN/HRS		
CONTACT	Rated 10 AM or 250 VAC (1/8 HP @ 120			
RATING	1/4 HP @ 240 VAC 240 VA @ 240 VAC			
LIFE	10 million operations with no load 100,000 operations with: 10 AMPS at 30 VDC (or less) or 10 AMPS at 250 VAC (or less)			
CONTACT MATERIAL	Silver Cadmium Oxide			
TEMPERATURE RATING	0° to 140°F (-18°C to 60°C)			
noise Immunity	Showering ARC per NEMA ICS 2-230. In addition, the 422A will withstand a voltage surge of 4500 volts for 50 μ sec. without damage.			
MOUNTING	Plug-in octal base Options: Surface mounting socket DIN rail mounting socket Plug-in socket kit (8-pin)			
	Panel mounting kit 8-pin panel socket w/rear facing terminals			
POWER		pt power from 24 to 240 VAC, 50 or 6, -20%) 24 VDC (+20%, -20%)		
REQUIRE- MENTS	AC	Inrush - 1.5 Amps Power required - 1.2 Watts		
MENTS	DC	Maximum ripple at 60 Hz - 5% Current required - 50 mA Power required - 1.2 watts		
MINIMUM SETTING	2% of range, with the exception of 50 mSEC on the seconds range.			
Setting Accuracy	+/-5% of range			
REPEAT ACCURACY	Varies as a function of temperature. Any voltage (constant temperature): $\pm 0.5\%^*$ Any voltage (32° F to 140° F): $\pm 1.5\%^*$ Any voltage (0° F to 140° F): $\pm 2.0\%^*$ *Variation from average actual time			
	а	0 to 20 mSEC power interruption: guaranteed no reset		
RESET	b	20 to 65 mSEC; it may reset (40 mSEC typical reset)		
	С	Over 65 mSEC guaranteed to reset		
WEIGHT	7 ounces			


OPERATION

Repeat Cycle: Timing begins when power is applied to terminals 2 & 7. The timer operates continuously through its two timing ranges (T1 and T2), one after the other, transferring the relay contacts as it times out of each range. The relay will energize during either the T1 or T2 time depending on the particular model specified (see accompanying chart). There is no start circuit and the timer resets on power interruption.

Single Cycle: Timing begins when power is applied to terminals 2 & 7. The timer will operate for one cycle only, that is, the relay will energize during either the T1 or T2 time depending on the particular model specified (see accompanying chart). Power must be removed from terminal 2 or 7 to reset the timer. The timer will reset on power interruption.

MODEL NUMBER >>>>> 422A				
Range				
Six dial-selected ranges (1 or 10 SEC/MIN/HRS) 100				
Six dial-selected ranges (5 or 50 SEC/MIN/HRS) 500				
Voltage & Frequency				
24 to 240 VAC (50/60 Hz) and 24 VDC F				
12 VDC E				
Sequence				
OFF/ON (Relay energized during T2)	1			
ON/OFF (Relay energized during T1)	3			
Cycle Ty	/pe			
Repeat Cycle 0				
Single Cycle				
F	eatu	ures		
Standard Tim			Х	
Specia				
Accessories				
8-Pin surface/DIN rail socket 0000-825-85-00				
Hold down for above socket 0422-025-02-00				
Panel mounting kit consisting of gasket and 2 clamps 0328-260-02-00				
Plug-in socket kit (8-pin) 0319-261-45-00				
8-Pin panel socket w/rear facing terminals 600-3-0011				

WIRING



Power Supply

Model	T1	T2	
F1	de-energized	energized	
F3	energized	de-energized	

Τ2