

## **VS3 Series Retroreflective Mode Sensors**

Miniature self-contained sensors



#### **VS3 Series Retroreflective Mode Sensor Features**

- Extremely compact self-contained miniature sensor
- · Coaxial optics eliminate "blind" area at close range
- Visible red sensing beam (both polarized and non-polarized versions)
- Range to supplied retroreflector is 0 to 250 mm (up to 10")
- 10 to 30V dc operation
- · Choice of integral cable or quick-disconnect connector
- · 3-wire hookup; output load capacity to 50 mA
- · Choose models with NPN (sinking) or PNP (sourcing) output
- · Choose dark- or light-operate models

User Application Notes:

- The VS3...XLP series should be used for general sensing applications like packages, small parts, mirror-like surfaces, or documents. They are most effective when used with the supplied micro-prism reflector.
- When using glass bead tape, (e.g., 3M model 6870), non-polarized models (...XLV) must be used. These models should also be considered when a glass lens (as in the LP models) is not permitted in the sensing environment.



• For non-polarized sensors, an object's surface reflection (e.g., polished stainless steel), may be more reflective than low-grade retro-reflective tape, and "bright" object transition may never be detected by the non-polarized sensor.





#### **VS3 Series Retroreflective-Mode Sensors**

Models		Cable	Supply Voltage	Output Type	Excess Gain	Beam Pattern
Non-Polarized Models					1000	
VS3AN5XLV VS3AN5XLVQ	250 mm (10") using BRT32X20AM retro target (supplied)	2 m (6.5') 3-Pin Pico QD	10 to 30V dc	NPN Light Operate	E VS3XLV X C Retroreflective Mode E 100 - Retroreflective Mode E S S S S S S S S S S S S S S S S S S	15 mm 10 mm 5 mm 10 mm 1
VS3RN5XLV VS3RN5XLVQ		2 m (6.5') 3-Pin Pico QD		NPN Dark Operate		
VS3AP5XLV VS3AP5XLVQ		2 m (6.5') 3-Pin Pico QD		PNP Light Operate		
VS3RP5XLV VS3RP5XLVQ		2 m (6.5') 3-Pin Pico QD		PNP Dark Operate		
Polarized Models					1000	
VS3AN5XLP VS3AN5XLPQ	250 mm (10") using BRT32X20AM retro target (supplied)	2 m (6.5') 3-Pin Pico QD	10 to 30V dc	NPN Light Operate	E X VS3XLP X Polarized	15 mm
VS3RN5XLP VS3RN5XLPQ		2 m (6.5') 3-Pin Pico QD		NPN Dark Operate		
VS3AP5XLP VS3AP5XLPQ		2 m (6.5') 3-Pin Pico QD		PNP Light Operate		
VS3RP5XLP VS3RP5XLPQ		2 m (6.5') 3-Pin Pico QD		PNP Dark Operate		

# **VS3 Series Retroreflective Mode**

### **VS3 Series Overview**

VS3 Series miniature self-contained sensors are designed for retroreflective sensing in small areas previously accessible only to remote or fiber optic models. Typical applications include mounting on small feeder tracks, packaging machines, and conveyors, where larger sensors will not fit.

The coaxial optics of the VS3 allow the retroreflective target to be placed as close to the sensor lens as needed — there is no "blind" response area, as is typical of most retroreflective sensors. The VS3 is supplied with a Banner model BRT32X20AM retroreflective target (see right). The specifications shown on page 1 assume use of this target.

Other retroreflective materials may be substituted. For example, using the standard BRT-3 target, the range becomes 400 mm (16"); standard BRT-THG retroreflective tape yields a 150 mm (6") range. Contact Banner Engineering for sensing performance when using other retroreflective targets.




Figure 1. Retroreflective target, model BRT-32X20AM (supplied with each sensor)

## **VS3 Series Specifications**

Supply Voltage and Current	10 to 30V dc (10% maximum ripple) at less than 25 mA (exclusive of load)				
Supply Protection Circuitry	Protected against reverse polarity and transient voltages				
Output Configuration	SPST solid-state switch Choose NPN (current sinking) or PNP (current sourcing) models Choose light operate (N.O.) or dark operate (N.C.) models				
Output Rating	50 mA maximum  OFF-state leakage current: < 1 microamp at 24V dc  ON-state saturation voltage: < 0.25V at 10 mA dc; < 0.5V at 50 mA dc				
Output Protection Circuitry	otected against false pulse on power-up and continuous overload or short circuit of outputs erload trip point ≥ 100 mA				
Output Response Time	Time 1 millisecond ON and OFF (NOTE: 150 millisecond delay maximum on power-up: output does not conduct during this time)				
Repeatability	160 microseconds				
Indicators	Two LEDs: Green and Yellow Green ON steady: power to sensor is ON Green flashing: output overload Yellow ON steady: light is sensed				
Construction	XLV Models: Black ABS housing with acrylic lens XLP Models: Black ABS housing with glass lens and acrylic cover				
Environmental Rating	IEC IP67; NEMA 6				
Connections	2 m (6.5') attached cable: three #28 ga stranded conductors with PE insulation; PVC outer cable jacket; or 3-pin Pico-style threaded quick-disconnect fitting. QD cables are ordered separately.				
Operating Conditions	Temperature: -20° to +55°C (-4° to +131°F)  Maximum Relative Humidity: 80% at 50°C (non-condensing)				
Vibration and Mechanical Shock					
Application Notes	M3 stainless steel mounting hardware included. Optional mounting brackets are available (page 4).				
Certifications	C€				

# **VS3 Series Retroreflective Mode**

## **VS3 Series Sensor Hookups**

#### **Sensors with NPN Outputs Sensors with PNP Outputs Cabled Models Cabled Models** 10-30V dc 10-30V dc bn bu **Quick-Disconnect Models Quick-Disconnect Models** 10-30V dc 10-30V dc bu bk Load Load

### **VS3 Series Retroreflective Mode Sensor Dimensions**

