



**DC22 Concentric  
Precision Turns Counting Dial/Pot Combination**

[HOME PAGE](#)

[Linear Motion Potentiometers](#)

[Single Turn Potentiometers](#)

[Multi-Turn Potentiometers](#)

[Industrial Joysticks](#)

[Foot Controllers](#)

[Valve Actuators](#)

[Turn Counting Dials](#)

[Cross Reference](#)

[ETI Systems Sales Reps](#)

[ETI Systems Distributors](#)



**DC22 Pot/Turns Counting Dial Combination**

- Uses ETI Systems Potentiometer [MW22](#)
- Resistance Range 100 to 100K ohms
- Resistance Tolerance:  $\pm 5\%$  standard ( $\pm 1\%$  special order)
- Linearity Tolerance:  $\pm 0.25\%$  standard ( $\pm 0.1\%$  special order)
- Power Rating: 2 Watts (10 turn)
- Counts 10 turns (000 to 999 counts)
- Accuracy:  $\pm 0.35\%$  of Voltage Ratio
- Repeatability:  $\pm 0.02\%$  or Resolution of Pot
- High Temp. Black Plastic Housing.
- Over the Center Lock
- Diameter - 1-1/16"; Extension from Panel - 1.24"
- Operating Temperature -30°C to +85°C

RoHS/WEEE

Contact  
ETI Systems at:  
(760) 929-0749  
[eti@etisystems.com](mailto:eti@etisystems.com)

**Request For Quotation (Requires User Registration)**

**Please Describe Requirements Below:**

**Quantity Required**

**Date Required**

**Return to: [Turn-Counting Dials Selection Guide](#)**

Call ETI Systems at **(760)929-0749** to order by phone  
or for assistance with your custom application