






AP Series — Miniature Pilot Lights

Miniature Pilot Lights with Super Bright LEDs

Key features of AP series include:

- Long service life, low maintenance
- Space saving miniature style
- Dome or flat lens models
- Built-in current-limiting resistor and reverse polarity protection diode
- Five illumination colors: red, green, amber, yellow, and white
- AC adaptor (120V AC and 240V AC) and DC-DC Converter (110V DC) options on 12mm and 16mm units



Switches & Pilot Devices

A5





Specifications	Lamp	Built-in LED with current limiting resistor
	Operational Voltage	6, 12, 24VDC (full voltage), 110/120, 220/240VAC, (transformer) 110VDC (with converter)
	Current Ratings	AP8: 6VDC/18mA, 12VDC/18mA, 24VDC/12mA AP1: 6VDC/18mA, 12VDC/18mA, 24VDC/12mA AP2: 6VDC/33mA, 12VDC/22mA, 24VDC/11mA AP6: 6VDC/33mA, 12VDC/22mA, 24VDC/11mA
	Operating Temp.	-20°C to +55°C
	Operating Humidity	45 to 85% RH
	Insul. Resistance	100MΩ min. (500V DC megger) Between live and dead parts
	Rev. Withstand Voltage	AP2/AP6: 100V AP1/AP8: 200V
	Solder Terminal	Soldering 260°C maximum (5 sec.)
	Degree of Protection	AP8: IP40 (dustproof) Other Series: IP65 (oiltight)

Optional Adaptors/Converters		AC Adaptor	DC-DC Converter
	Applicable Units	AP2 & AP6 (with 6V LED only)	
	Operating Voltage	110/120VAC 50/60 Hz 220/240VAC 50/60 Hz	110V DC (90 to 140V DC)
	Power Consumption	1.6 VA maximum	1W maximum
	Insulation Voltage	250 V AC	140V DC
	Insulation Resistance	10MΩ min. (500V DC megger) Between live and dead parts	
	Dielectric Strength	2,000V AC, 1 minute Between live/dead parts 2,000V AC, 1 minute Between terminals	2,000V AC, 1 minute Between live/dead parts 1,500V AC, 1 minute Between terminals

Available as one piece only (replacement LEDs are not available).

Miniature Pilot Lights (Assembled)

Part Numbers: AP Miniature Pilot Lights

Appearance	Lens Style	Operating Voltage	Part Numbers
AP8 Series - ø 8mm 	Dome	6V DC +/- 5% 12V DC +/- 10% 24V DC +/- 10%	AP8M266-② AP8M211-② AP8M222-②
	Flat	6V DC +/- 5% 12V DC +/- 10% 24V DC +/- 10%	AP8M166-② AP8M111-② AP8M122-②
AP1 Series - ø 10mm 	Dome	6V DC +/- 5% 12V DC +/- 10% 24V DC +/- 10%	AP1M266-② AP1M211-② AP1M222-②
	Flat	6V DC +/- 5% 12V DC +/- 10% 24V DC +/- 10%	AP1M166-② AP1M111-② AP1M122-②
AP2 Series - ø 12mm 	Dome	6V DC +/- 5% 12V DC +/- 10% 24V DC +/- 10%	AP2M266-② AP2M211-② AP2M222-②
	Flat	6V DC +/- 5% 12V DC +/- 10% 24V DC +/- 10%	AP2M166-② AP2M111-② AP2M122-②
AP6 Series - ø 16mm 	Dome	6V DC +/- 5% 12V DC +/- 10% 24V DC +/- 10%	AP6M266-② AP6M211-② AP6M222-②
	Flat	6V DC +/- 5% 12V DC +/- 10% 24V DC +/- 10%	AP6M166-② AP6M111-② AP6M122-②


② Color Code

Color	Code
Amber	A
Green	G
Red	R
White	W
Yellow	Y



1. In place of ②, specify the color code.
2. For dimensions, see page A5-212
3. For accessories, see page A5-212.

Part Numbers: Optional AC Adaptors and DC-DC Converters (for AP2 and AP6 only)

Appearance	Style	Voltage	Part Numbers	
			Used with AP2 Series	Used with AP6 Series
	AC Adaptor	110/120V AC 220/240V AC	AP2-0126D AP2-0246D	AP6-0126D AP6-0246D
	DC-DC Converter	110V DC (90-140V DC)	AP2-016DD	AP6-016DD

Secondary Voltage = 6V



1. Optional AC adaptors and DC-DC converters snap onto the back of AP2 or AP6 pilot lights.
2. AC Adaptors and DC-DC Converters step down to 6V.
3. For dimensions, see page A5-213.

Dimensions — AP Series

Pilot Lights (AP Series)

Style	AP8		AP1		AP2			AP6		
	Flat	Dome	Flat	Dome	Flat	Dome	w/ Adaptor or Converter	Flat	Dome	w/ Adaptor or Converter
Panel Cut-out	Ø 0.319" (+0.0118, -0) 8.1mm (+0.3, -0)		Ø 0.398" (+0.0118, -0) 10.1mm (+0.3, -0)		Ø 0.480" (+0.0118, -0) 12.2mm (+0.3, -0)			Ø 0.638" (+0.0118, -0) 16.2mm (+0.3, -0)		
Outside Dimension	Ø 0.386" (9.8mm)		Ø 0.472" (12mm)		Ø 0.551" (14mm)		□ 0.709" (18mm)	Ø 0.709" (18mm)		□ 0.709" (18mm)

A5

Switches & Pilot Devices

