

Front side mounting, fuseh. 5 x 20 mm/6.3x32 mm, with or without voltage selector (series-parallel)

Standard- or Medical-Filter





Fuse drawer and voltage selector insert must be ordered separately.

C14



70° C





# **Description**

- Panel Mount:
- Screw-on from front side
- 4 Functions:

Appliance Inlet, Fuseholder with interchangeable fuse drawer for Fuselinks 5 x 20 mm or 6.3 x 32 mm 1- or 2-pole, Voltage selector (seriesparallel), Line filter in standard and medical version

- Quick connect terminals 4.8 x 0.8 mm
- Alternative: version without line filter KE

- VDE License Number: 40004665 (FKA, FKB)
- UL License Number: E72928 (FKA, FKB)

#### **Characteristics**

- All single elements are already partially wiredFor added safety "Extra-Safe" fuse drawers are available Fuse drawer meets requirements of medical standard IEC/EN 60601-1 The fuse drawer can only be opened with the aid of a tool The fuseholder is accessible from the equipment front
- Qualified for use in equipment according IEC/EN 60950

#### References

General Product Information

Appliance-Inlet/-Outlet

#### Weblinks

Approvals, RoHS, CHINA-RoHS, e-Store, SCHURTER-Stock-Check, Distributor-Stock-Check

C14 acc. to IEC/EN 60320-1,


Technical Data	
Ratings IEC	1 - 10 A @ Ta 40 °C / 250 VAC; 50 Hz
Ratings UL/CSA	1 - 10 A @ Ta 40 °C / 125 VAC; 60 Hz
Leakage Current	standard < 0.5 mA (250 V / 60 Hz) medical < 5 µA (250 V / 60 Hz)
Dielectric Strength	> 1.7 kVDC between L-N > 2.7 kVDC between L/N-PE Test voltage (2 sec)
Allowable Operation Temp.	-25 °C to 85 °C
Climatic Category	25/085/21 acc. to IEC 60068-1
Degree of Protection	from front side IP 40 acc. to IEC 60529
Protection Class	Suitable for appliances with protection class I acc. to IEC 61140
Terminal	Quick connect terminals 4.8 x 0.8 mm
Panel Thickness s	Screw-on: max 8mm Mounting screw torque max 0.5 Nm
Material: Housing	Thermoplastic, black, UL 94V-0


	UL 498, CSA C22.2 no. 42 (for cold conditions) pin-temperature 70 °C, 10 A, Protection class I
Fuseholder	1 or 2 pole, Shocksafe category PC2 acc. to IEC 60127-6, for fuse-links 5 x 20 or 6.3 x 32 mm
Rated Power Acceptance @ Ta 23 °C	5 x 20: 2.5W (1 pole)/ 2W (2-pole) per pole 6.3 x 32: 3.15W (1 pole)/ 2.5W (2-pole) per pole
Power Acceptance @ Ta > 23°C	Admissible power acceptance at higher ambient temperature see derating curves
Voltage selector	series-parallel, 4, 3 or 2 switch positions or usable as 2-pole change-over switch
Line Filter	Standard and Medical Version, IEC 60939, IEC 60601-1, UL 1283, UL 544, EN 133 200, CSA C22.2 no. 8 Technical details
MTBF	> 1'400'000 h acc. to MIL-HB-217 F




#### **Dimensions**

Length 69 mm








#### **Technical Data of Filter-Components**


Rated Current [A]	Filter-Type	Inductances L [mH]	Capacitance CX [nF]	Capacitance CY [nF]	<b>R</b> [ <b>M</b> Ω]
1	Standard Version	2 x 10	68	2.2	-
2	Standard Version	2 x 4	68	2.2	-
4	Standard Version	2 x 1.5	68	2.2	-
6	Standard Version	2 x 0.8	68	2.2	-
10	Standard Version	2 x 0.3	68	2.2	-
1	Medical Version (M5)	2 x 10	68	-	1
2	Medical Version (M5)	2 x 4	68	-	1
4	Medical Version (M5)	2 x 1.5	68	-	1
6	Medical Version (M5)	2 x 0.8	68	-	1
10	Medical Version (M5)	2 x 0.3	68	-	1
2	Medical Version (M80)	2 x 4	68	0.47	1

# **Diagrams**

Standard version


Medical version








- 1) Line
- 2) Load
- x) External connection to be made
- by customer

## **Derating Curves**











# **Attenuation Loss**

Standard version


1 A




## 2 A



## 4 A




# 6 A




- - - - differential mode \_\_\_\_\_ common mode

# 10 A




## Medical version (M5)


1 A




# 2 A




4 A



6 A



# 10 A



# **Variants**

Fuse drawer and voltage selector insert must be ordered separately.

Rated Current [A]	Filter-Type	Fuseholder	Order Number
1	Standard Version	1 pole	CE16.5100.151
2	Standard Version	1 pole	CE26.5100.151
4	Standard Version	1 pole	CE36.5100.151
6	Standard Version	1 pole	CE45.1100.151
6	Standard Version	1 pole	CE46.5100.151
10	Standard Version	1 pole	CE66.5100.151
1	Standard Version	2-pole	CE10.6100.151
2	Standard Version	2-pole	CE20.6100.151
4	Standard Version	2-pole	CE30.6100.151
6	Standard Version	2-pole	CE40.6100.151
10	Standard Version	2-pole	CE60.6100.151
1	Medical Version (M5)	2-pole	CEG0.6100.151
2	Medical Version (M5)	2-pole	CEA0.6100.151
4	Medical Version (M5)	2-pole	CEC0.6100.151
6	Medical Version (M5)	2-pole	CEE0.6100.151
10	Medical Version (M5)	2-pole	CEL0.6100.151



Rated Current [A]	Filter-Type	Fuseholder	Order Number
2	Medical Version (M80)	2-pole	CEB0.6100.151

Packaging unit

10 Pcs

# **Required Accessory**

## Description



#### Jumper Wire 1

Connection with Starnded Cable

Type B, 100	0881.0074
Type B, 100	0881.0075
Type A, 100	0881.0076
Type A, 100	0881.0077



Drawer for fuse links 5x20mm resp. 6.3x32mm

5 x 20, 2-pole	4305.0001
5 x 20, 1 pole	4305.0006
6.3 x 32, 2-pole	4305.0011
6.3 x 32, 1 pole	4305.0016



Voltage Selectors Insert 1 Voltage Selector Insert to KE, CE, KG, CG



3 or 4 switch positions	4305.0048.00
1, 3 or 4 switch positions, 100, 120, 220, 240	4305.0048.01
3, 3 or 4 switch positions, 130, 110, 240, 220	4305.0048.02
2, 2 switch positions, 110, 220	4305.0048.03

#### **Accessory**



Assorted Covers Rear Cover

0859.0108



Cord retaining kits Cord retainning strain reliefe

4700.0001 Flat head, A