


Modular Type - Accessories

SOFT START-UP VALVE SERIES (N)AV 2000, 3000, 4000 1/4, 3/8, 1/2 "

- Combined Soft Start and Dump Valve
- Compatible with Modular Series FRL
- Large Cv Factor
- Low Power
- Air Supply and Exhaust can be operated manually









The NAV valve pictured together with an NAW series Filter/Regulator and an NAN series Silencer. (To order these items, see Air Preparation section {NAW} and Valves section {NAN}

TECHNICAL **SPECIFICATIONS**

Model		NAV2000	NAV3000	NAV4000	
Port Size		1/4	3/8	1/2	
Proof Pressure		1.5MPa / 220PSI			
Operating Pressure Range			1MPa / 145PSI		
Pressure Gauge Port Size			√s		
Ambient and Fluid Temperature			0 ~ 60°C* / 32~140°F		
$ \begin{array}{c} P \! \rightarrow \! A \\ \hline A \! \rightarrow \! R \end{array} $		1.19	2.20	3.60	
		A→R	1.39	2.89	4.49
Weight (kg)			0.27	0.48	0.74
Electrical Spec	Coil Rated Voltage		110, 240V AC (50/60Hz); 12, 24V DC		
	Allowable Voltage Fluctuation		-15% to +10% of rated voltage		
	Coil Insulation Type		Type B equivalent (130°C)		
	Apparent Power AC (Power Consumption)	Inrush	5.6VA (50Hz)		
		Holding	3.4VA (2.1W)/50Hz		
	Power Consumption DC		1.8W		
	Electrical Connector		DIN 43650 (industrial form)		
	Semi-Standard Spec		With indicator light and surge voltage suppressor		
Pilot Valve Manual Override			Non-locking push type		

*Use dry air when temperature is low.





-Rc(PT)* Remove (N) when orderingG(PF)* Remove (N) when ordering
- NNPT

PORT SIZE -

- 02 ... ½ (NAV2000 only) 03 ... ½ (NAV3000 only) 04 ... ½ (NAV4000 only)

COIL RATED VOLTAGE

- 3110V AC (50/60Hz)
-240V AC (50/60Hz)
-24V DC 612V DC

INDICATOR LIGHT AND

SURGE VOLTAGE SUPRESSOR

-None
-With surge voltage
- suppressor only
 ZWith Indicator light and surge voltage suppressor



