


## 1337775-4 Product Details



**1337775-4**

TE Internal Number: 1337775-4

 [Active](#)

### RF Coax Cable Assemblies

 [Converted to EU RoHS/ELV Compliant \(Statement of Compliance\)](#)

#### Product Highlights:

- 2 Connectorized Ends
- RF Coax Cable Assemblies Application
- Connector Type = BNC Straight Plug to BNC Straight Plug
- Assembly Length = 1.50 M
- Coaxial Cable Type (RG/U or Mfg.) = 59

[View all Features](#)

### Documentation & Additional Information

#### Product Drawings:

- None Available

#### Catalog Pages/Data Sheets:

- None Available

#### Product Specifications:

- None Available

#### Application Specifications:

- None Available

#### Instruction Sheets:

- None Available

#### CAD Files:

- None Available

#### Additional Information:

- [Product Line Information](#)

#### Related Products:

- [Tooling](#)

### Product Features (Please use the Product Drawing for all design activity)

#### Product Type Features:

- [Connector Type](#) = BNC Straight Plug to BNC Straight Plug

#### Electrical Characteristics:

- Connector Impedance ( $\Omega$ ) = 75

#### Body Related Features:

- [Number of Connectorized Ends](#) = 2
- [Assembly Length \(M \[ft\]\)](#) = 1.50 [4.921]
- [Body Plating](#) = Nickel

#### Contact Related Features:

- Center Contact Plating = Gold

#### Configuration Related Features:

- [Coaxial Cable Type \(RG/U or Mfg.\)](#) = 59

#### Industry Standards:

- [RoHS/ELV Compliance](#) = RoHS compliant, ELV compliant
- [Lead Free Solder Processes](#) = Not relevant for lead free process
- RoHS/ELV Compliance History = Converted to comply with RoHS directive

#### Operation/Application:

- Application = RF Coax Cable Assemblies

#### Other:

- Brand = Greenpar