


1337780-2 Product Details



No Image Available

1337780-2

TE Internal Number: 1337780-2



Active

RF Coax Cable Assemblies

 [Converted to EU RoHS/ELV Compliant \(Statement of Compliance\)](#)

Product Highlights:

- 2 Connectorized Ends
- RF Coax Cable Assemblies Application
- Connector Type = BNC Straight Plug to BNC Straight Jack
- Assembly Length = .50 M
- Coaxial Cable Type (RG/U or Mfg.) = 59

[View all Features](#)

Documentation & Additional Information

Product Drawings:

- [BNC PLUG - BNC JACK CABLE ASSEMBLY](#) (PDF, English)

Catalog Pages/Data Sheets:

- None Available

Product Specifications:

- None Available

Application Specifications:

- None Available

Instruction Sheets:

- None Available

CAD Files:

- None Available

Additional Information:

- [Product Line Information](#)

Related Products:

- [Tooling](#)

[List all Documents](#)

Product Features (Please use the Product Drawing for all design activity)

Product Type Features:

- [Connector Type](#) = BNC Straight Plug to BNC Straight Jack

Electrical Characteristics:

- Connector Impedance (Ω) = 75

Body Related Features:

- [Number of Connectorized Ends](#) = 2
- [Assembly Length \(M \[ft\]\)](#) = 0.50 [1.640]
- [Body Plating](#) = Nickel

Contact Related Features:

- Center Contact Plating = Gold

Configuration Related Features:

- [Coaxial Cable Type \(RG/U or Mfg.\)](#) = 59

Industry Standards:

- [RoHS/ELV Compliance](#) = RoHS compliant, ELV compliant
- [Lead Free Solder Processes](#) = Not relevant for lead free process
- RoHS/ELV Compliance History = Converted to comply with RoHS directive

Operation/Application:

- Application = RF Coax Cable Assemblies

Other:

- Brand = Greenpar